

# MODIFY

The MODIFY direct command provides direct access to Entire Operations definition screens containing current values of the selected object. When you have modified the object, press PF3 (End) to return to the screen from which you issued the MODIFY command.

The command format is:

<b>MODIFY</b>	{	<b>USER</b>	[userid ]	}
		<b>NETWORK</b>	[network ]	}
		<b>JOB</b>	[job ] [network ]	}

where:

Parameter	Description
job	Name of the job to be modified.
network	Name of the network to be modified.
userid	Entire Operations user ID.
*	Opens a selection window with a list of available object names (see explanation of LIST).

If you issue the MODIFY command from the Network and Job Maintenance facility and omit the **job** or **network** name parameter, the current network and/or job is selected.

For further information, please see Adding or Modifying a Job Definition in the section Job Maintenance Facility of the Entire Operations User's Guide.